



### Audio Sound RF Controller DC 12V-24V + 6-Key Remote Control

Product Model: #BY-CON-RFMU

Manufactured by: TopLedLight

Category: LED Controller

Retail price: ~~US\$24.99~~

**Wholesale Price: US\$  21.99**

MOQ: 1 PCS

Net Weight: 203g

Shipping: Free Shipping World Wide

Payment methods: Paypal, Western Union, Wire Transfer

For Bulk Orders Discount, please email info@TopLEDlight.com

 [Ask Questions](#)

### Description:

#### Product Description

This RF Audio controller adopts the advanced micro control unit, it is used for controlling a variety of lamp whose source of light is LED. For instance, point source of light, flexible light strip, wall washer lamp, glass curtain wall light and so on. At the same time, it has many advantages such as convenient connection, simplicity to use and others. According to the actual need of customers, it can carry out jumpy changing, gradual changing, stroboflash and other effects of change.

#### Specification

- Supply Voltage: DC 12V - 24V
- Output: 3 Channels
- Connecting Mode: Common anode
- Transmission/Receiving Frequency: 433Mhz
- External dimension: L130 X W64 X H24
- Package Size: L145 X W95 X H50
- Static Power Consumption: <1W
- Output Current: Output Power: 12V: <144W, 24V: <288W

#### Direction for Use

- 1. Connect the load wire at first, following by the power wire; Please ensure short circuit can not occur between connecting wire before you turn on the power;
- 2. Adopt RF control, there are six buttons altogether, and every key-press function is as follows:  
 ON/OFF: any state to close load output;  
 MODE: it is the style/color function key, could choose different color changes, 13 total;  
 Button B+: Brightness control of the output signal each press changing speed +1, 256 total.  
 Button B-: each press brightness changing -1;  
 Button S+: each press changing speed +1, 100 total;  
 Button S-: each press changing speed -1.

▪ Note: When the external microphone input and audio signal input at the same time, system will process the audio signal.

▪ 3. Standard changes function as the following form:

No	Patters	Remarks
1	Static Red	Brightness is adjustable, Speed is unadjustable
2	Static Green	
3	Static Yelow	
4	Static Blue	
5	Static Purple	

6	Static Cyan	
7	Static White	
8	Three-color jumpy changing	Brightness and Speed are adjustable
9	Seven-color jumpy changing	
10	Three-color gradual changing	Speed is adjustable
11	Seven-color gradual changing	
12	Three-color jumpy changing (external signal)	Speed changes with the voice swing, brightness controlled with the volume, the high volume is, the greater the brightness
13	Seven-color jumpy changing (external signal)	

---

### Packing List

**Full Page:** [http://www.topledlight.com/audio-sound-rf-controller-dc-12v24v-6key-remote-control\\_p361.html](http://www.topledlight.com/audio-sound-rf-controller-dc-12v24v-6key-remote-control_p361.html)

---

**TopLEDlight**® is a leading China based LED lighting products wholesaler: LED lights, strips, drivers, controllers, power supplies and more.